

CS8 Wiring

Note:

H/Lamp off – Switches off H/Lights and activates kill switch to stop engine.

Kill Switch:

Blue/White – Black/White

Engine Run (Static) – Open circuit

Engine Stop(Activated) – Closed circuit

H/Lamp:

Power to H/Lamp – Red

High Beam – Yellow

Low Beam – Green

Tail/Park Lamp – Blue

Turn Switch:

From Flasher Relay – Orange

R/H – Dark Green

L/H – Dark Brown

Horn:

Pink – From Horn

Black – Ground/Earth